

# THE CAT® INV1250

## PORTABLE INVERTER GENERATOR

Running Power	1100 Watts
Starting Power	1250 Watts
AC Output	120 V @ 60 Hz
Run Time @ 50% Load	4 hrs
Fuel Tank Nominal Capacity	0.82 gal / 3.18L
Starting Method	Pull
Engine Displacement	60 cc
Engine Type	OHV
Engine Speed	Variable RPM
Fuel Type	87 octane or greater unleaded gasoline* (no more than 10% ethanol)
Recommended Oil	SAE30 or 10W-30
Lubrication Method	Splash
Power Outlets	1x 5-20R 1x 5V 2.1A USB 1x 5V 1.0A USB
Battery Type	-
Voltage Regulation	Inverter Type
Fuel Gauge	Dial Gauge
Warranty	3-Year**
USB	1x 1.0A 5V and 1x 2.1A 5V

\* Fuel stabilizer should also be used for storage  
 \*\*2-year limited, 3-year limited when registered within 30 days

For more information on our current generator lineup, visit: [cat.com/portablepower](http://cat.com/portablepower)

**CONTROL PANEL WITH LED ILLUMINATION**  
for better visibility in low-light conditions

**LED NOTIFICATIONS**  
for Low Oil, Overload and Running

**DUAL USB PORTS**  
to charge phones, tablets and laptops

**DOUBLE THE POWER**  
by connecting a second INV1250

**INTUITIVE START/STOP SWITCH**  
with integrated choke

**CARBON MONOXIDE SHUTDOWN**  
to keep you and your family safe

**AUTOMATIC LOW-OIL SHUTDOWN PROTECTION**  
provides peace of mind for long-lasting operation

**SERVICE WITH EASY ACCESS**  
to air filter and fuel drain

**NO MESS**  
unique no-drip oil fill/drain design

**ENGINE SMART CONTROL (ESC)**  
automatically adjusts power to your exact needs – no more, no less

